


# VOLTT®

## GENERATOR VG300

### Technical Specifications Card

|                        |  |                                  |
|------------------------|--|----------------------------------|
| <b>Product Picture</b> |  |                                  |
| <b>Generator</b>       | Model NO.  | VG300                            |
|                        | Type   | Brush Single - Phase             |
|                        | Voltage Regulate   | Inverter + Silent                |
|                        | Rated AC voltage (V)   | 220V / 60HZ                      |
|                        | Alternator   | 100% Copper                      |
|                        | Rated AC output (KW)   | 3.5KW                            |
|                        | Peak AC output (KW)  | 4.0KW                            |
|                        | Fuel tank capacity   | 10L                              |
|                        | Phase  | Single                           |
|                        | Run time (50%- 100% load)  | 9.0 - 5.5h                       |
|                        | Operation Noise Level (7m) dB(A)   | 58                               |
|                        | Power factory COS  | 1.0                              |
| <b>Engine</b>          | Model  | SV230                            |
|                        | Type   | OHV Forced Air - cooled 4-Stroke |
|                        | Bore x Stroke (mm)   | 70x58                            |
|                        | Displacement (ml)  | 223cc                            |
|                        | Max. output (kw/rpm)   | 5.5/3600                         |
|                        | Fuel type  | GASOLINE                         |
|                        | Fuel consumption   | 374g/kw/h                        |
|                        | Oil  | SF or higher grade               |
|                        | Oil capacity (L)   | 1.2                              |
|                        | Ignition System  | Transistorized                   |
|                        | Starting system  | E-START                          |
| <b>Control Panel</b>   | Fuel gauge   | Yes                              |
|                        | Voltmeter  | Digital meter                    |
|                        | DC Output  | USB                              |
|                        | AC Circuit Breaker   | YES                              |
|                        | Parallel Function  | YES                              |
|                        | AC Socket  | UK type                          |
| <b>Weight</b>          | Net weight Kg  | 52                               |
|                        | Grass weight Kg  | 56                               |